

OPAMP selection and compare list							
Opamp	type	offset error in uV		offset		GBW	Slew Rate
	Bip. or Fet	min. or	max.	adjustable		product	
	or Cmos	average		Yes	No	MHz	V / usec
LT1037	B	20	60	1 + 8		45 - 60	11
OPA27	B	25	100	1 + 8		5 - 8	1.7 - 1.9
OPA37	B	25	100	1 + 8		45 - 60	11 - 12
OP27C	B	30	100	1 + 8		8	2.8
OP37C	B	30	100	1 + 8		40 - 60	11 - 17
OP07	B	30	75	1 + 5		0.4 - 0.6	0.1 - 0.3
OPA828	F	50	300		X	45	150
OPA827	F	75	150		X	22	28
OPA1611	B	100	500		X	40	27
OPA627	F	280	500	1 + 5		16	55
OPA637	F	280	500	1 + 5		80	135
LT1357	B	200	600	1 + 8		25	600
LT1360	B	300	1000	1 + 8		50	800
LT1363	B	500	1500	1 + 8		70	1000
AD817	B	500	2000	1 + 8		50	350
NE5534	B	500	2000	1 + 8		10	13
LF411	F	800	2000	1 + 5		2.7 - 3	8 - 13
OPA604	F	1000	5000	1 + 5		20	25
OPA134	F	1000	2000	1 + 8		8	15 - 20
LM741C	B	2000	6000	1 + 5		0.4 - 1	0.3 - 0.7
CA3140	C	5000	15000	1 + 5		4.5	9
CA3140A	C	2000	5000	1 + 5		4.5	9
LF356	F	3000	10000	1 + 5		5	12
LF357	F	3000	10000	1 + 5		20	50
TLC271	C	1100	12000	1 + 5		2.2	3 - 4
TL081	F	5000	15000	1 + 5		4	13